

DHI-ARD822-W2

Wireless Panic Button



- Two-way RF communication.
- Provides multiple LED colors to indicate different statuses.
- Cloud update and automatic recovery from update failure.
- Offers accidental press prevention.
- IP54 rated.

System Overview

Highly intuitive, the Wireless Panic Button supports multiple types of alarms to meet a wide variety of scenarios, triggering alarms for intrusions, fire, gas leaks, and more. It can also be used to notify the monitoring center and your loved ones that you are in need of medical aid, allowing them the opportunity to come to your assistance. Notices of alarm events are sent to the monitoring center to ensure a prompt response, and to you to keep you up to date.

Scene

Wireless Panic Button is ideal for use in apartments, villas, office buildings, stores and more.

Technical Specification

Function

Indicator Light	1 for multiple statuses (pairing, communication, and operation)	
Remote Update	Cloud update	
Button	2	
Signal Strength	Yes	
Low Battery Detection	Yes	
Battery Level Display	Displays battery level on app	


Wireless

Carrier Frequency	433.1 MHz-434.6 MHz
Communication Distance	Up to 800 m (2624.67 ft) in an open space
Communication Mechanism	Two-way
Encryption Mode	AES128

Frequency Hopping	Yes	
General		
Operating Temperature	−10 °C to +55 °C (+14 °F to +131 °F) (indoor)	
Operating Humidity	10%-90% (RH)	
Power Supply	1 × CR2032	
Battery Life	3 years (if used twice a week)	
Product Dimensions	55 mm × 36 mm × 14.2 mm (2.17" × 1.42" × 0.56") (L × W × H)	
Packaging Dimensions	95 mm \times 59.5 mm \times 30.5 mm (3.74" \times 2.34" \times 1.20") (L \times W \times H)	
Installation	Wall mount; portable	
Net Weight	18 g (0.04 lb)	
Gross Weight	48 g (0.11 lb)	
Certifications	CE	
Casing Material	PC + ABS	
Protection	IP54	
Technical		
Operating Current	28 mA	
Test Mode	Yes	

Ordering Information				
Туре	Model	Description		
Wireless Panic Button	DHI-ARD822-W2	3 types optional: Wireless Panic Button, Wireless Panic Button (with straps) and Wireless Panic Button (with bracket)		

Installation



Application







Alarm Hub

Wireless Panic Button

Dimensions (mm[inch])

